This Draft document contains all the errata discovered to date in *IEEE Std 1275-1994, Standard for Boot (Initialization Configuration) Firmware: Core Requirements and Practices*, including the three new ones discovered since draft#1.

To provide a context for the changes, the section header of all changed sections is listed in a box like this with a short rationale for the change (thanks to Mitch). Change bars indicate the modified text lines. To facilitate discussion and verification of the changes, deleted text is formatted as strike-out and added text is underlined. In the final document, the deleted text will be hidden and the added text unmarked (the change bars and these boxes will remain).

The IEEE editor will generate the rest of their boilerplate text, but we will have to provide the list of committee members at the time this document (P1275.7) is approved.

-John Rible, draft editor

Introduction

Editorial change: credit secretary properly.

<Unchanged body of introduction>

The following individuals were members of the P1275 Working Group at the time IEEE Std 1275-1994 ~~this document~~ was produced:

William M. (Mitch) Bradley, *Chair*
David M. Kahn, *Vice Chair*
John Rible, *Draft Editor*
Luan D. Nguyen~~**Mike Williams**~~, *Secretary*

Paul Fischer	Thanos Mentzelopoulos	Paul Thomas
Ron Hochsprung	David Paktor	Mike Tuciarone
	Michael Saari	Mike Williams

3.6.4 Expansion bus device class template

Editorial change: improve a possibly misleading short description.

Editorial change: add a section to describe the recommended technique for using existing standard words to handle bus-dependent register access semantics and explain why the user interface versions of those words are being removed.

A memory-mapped bus logically extends the processor's memory address space to include the *devices* on that bus, allowing the use of processor load and store cycles to directly address those devices. The details vary from bus to bus. This standard does not specify the adaptation of Open Firmware to any particular bus, but other related standards do so specify (see 2.1).

3.6.4.1 Bus-specific methods and properties

This subclause lists a set of *methods* that deal with requirements common to most memory-mapped buses. This subclause is intended as a suggested starting point for the development of complete sets of methods for particular buses; also see related standards, such as IEEE Std 1275.2-1994. The methods provide mapping services for establishing the correspondence between processor virtual and device *physical addresses,* allocation of DMA memory, and probing to locate *plug-in devices*.

map-in	(phys.lo ... phys.hi size -- virt)	Map the specified region; return a virtual address.
map-out	(virt size --)	Destroy mapping from previous **map-in**.
dma-alloc	(... size -- virt)	Allocate a memory region for later use.
dma-free	(virt size --)	Free memory allocated with **dma-alloc**.
dma-map-in	(... virt size cacheable? -- devaddr)	Convert virtual address to device bus DMA address.
dma-map-out	(virt devaddr size --)	Free DMA mapping set up with **dma-map-in**.
dma-sync	(virt devaddr size --)	Synchronize (flush) DMA memory caches.
probe-self	(arg-str arg-len reg-str reg-len fcode-str fcode-len --)	Evaluate FCode as a child of this node.

The following properties are specific to this class of *device node*:

"**ranges**"	Standard *property name* to define a bus-specific address translation. ~~device's physical address.~~
"**#address-cells**"	Standard *property name* to define the package's address format.
"**#size-cells**"	Standard *property name* to define the package's address *size* format.

3.6.4.2 Bus-specific register access words

Some expansion bus adaptors have characteristics that interfere with the semantics of the register-access words, **rb@**, **rb!**, **rl@**, **rl!**, **rw@**, and **rw!**. For example, some bus bridges swap bytes and others buffer their write operations. Bus packages for such devices shall substitute, as with **set-token**, conforming implementations of the register-access words during the evaluation of their childrens' FCode programs.

Such bus-specific register-access words can be written in terms of the "generic" register-access words, in the expectation that the parent bus will have substituted implementations of those words that handle any peculiar characteristics imposed by the parent bus. For example, suppose a bus adapter device supports a bus that reverses the order of doublets within quadlets. It can not predict the characteristics of its parent bus, for example, whether its parent bus reverses the order of bytes within a doublet. The FCode program for such a bus adapter would include a definition of a bus-specific quadlet register-read word that might look something like this:

```
: my-rl@ ( qaddr -- quad )  rl@ lwflip ;
```

When the FCode for this word's definition is evaluated, the definition of **rl@** that will get compiled-in will be the one that was substituted by the node of the parent bus. The node of the present bus adapter would then, before evaluating its childrens' FCode programs, have to perform a substitution that might look something like this:

```
['] my-rl@ h# 234 set-token
```

Because such a substitution takes place at the time of evaluation of an FCode program, it becomes problematical to ensure that the semantics of the intended register-access words will be visible at the user interface level. For this reason, it is recommended that device nodes for child-devices supply definitions for the register-access words that will bind the semantics that were substituted for the device's bus to the user interface name. Such a definition can be very simple, and might look something like this:

```
: rl@ ( qaddr -- quad )  rl@ ;
```

The net effect of such a definition would be that when the device is selected, and the user enters the name **rl@**, the user interface interpreter will find the name that occurs in the device's node; that name would be bound to the behavior that was installed in the FCode interpretation token-table at the time the device node's FCode was evaluated, causing the correct behavior to be executed.

3.6.5 Memory management device class template

Normative change: add a method that additional experience with IEEE Std 1275-1994 has shown to be required.

An MMU is a *device* that performs address translation between a CPU's *virtual addresses* and the *physical addresses* of some bus, typically the bus represented by the *root node*. In general, the details are both processor-specific and bus-specific. This standard does not specify the adaptation of Open Firmware to any particular MMU, but other related standards may so specify (see 2.1). This standard does not require the presence of an MMU.

This subclause lists a set of *methods* that deal with requirements common to most MMUs. This subclause is intended as a suggested starting point for the development of complete sets of methods for particular MMUs. The methods provide services for fine-grained control of the allocation and mapping of virtual addresses, particularly intended for use by *client programs* through the **call-method** *client interface* service (see also the "**mmu**" *property* of the **/chosen** node). In general, the use of these methods makes a client program system-specific; nevertheless, they are useful in some circumstances. The arguments and results shown are intended as guidelines; particular MMUs might require additional arguments or changes to the arguments shown.

The presence of an MMU node does not imply that the Open Firmware is necessarily using virtual-to-physical address translation hardware.

The following methods, defined in the glossary, are recommended for MMU *packages*:

claim	([virt] size align -- base)	Allocate (claim) addressable resource
release	(virt size --)	Free (release) addressable resource.
map	(phys.lo ... phys.hi virt size mode --)	Create address translation
unmap	(virt size --)	Invalidate existing address translation.
modify	(virt size mode --)	Modify existing address translation.
translate	(virt -- false | phys.lo ... phys.hi mode true)	Translate virtual address to physical address.

Additional requirements for the **claim** and **release** methods:
— The address format, *virt*, is a single-cell *virtual address*.
— The allocation length, *size*, is a single cell.
— The allocated resource is a region of virtual address space.

The following properties are recommended for MMU packages:

"**available**"	The property values are as defined for the standard "**reg**" format, with single-cell virtual addresses. The regions of virtual address space denote the virtual address space that is currently unallocated by the Open Firmware and is available for use by client programs.
"**existing**"	The value of this property defines the regions of virtual address space managed by the MMU in whose package this property is defined without regard to whether or not these regions are currently in use. The encodings of *virt* and *len* are MMU-specific.
"**page-size**"	The value of this property is the number of bytes in the smallest mappable region of virtual address space.

NOTE—Freeing virtual address space does not necessarily free any associated physical resource. The correct sequence of operations for freeing mapped memory is to first use **unmap**, thus destroying the translation. Then the physical memory and virtual address space can be freed with the **release** methods of the respective nodes.

3.8.3 "deblocker" support package

Normative change: add two methods to satisfy the requirements of existing deblocker support package implementations. IEEE Std 1275-1994 neglected to document this requirement.

Normative change: add an explicit clarification of a previously unstated requirement.

The "**deblocker**" *package* assists in the implementation of byte-oriented **read** and **write** *methods* for block-oriented or record-oriented *devices* such as disks and tapes. It provides a layer of buffering to implement a high-level byte-oriented interface "on top of" a low-level block-oriented interface. The "**deblocker**" *support package* defines the following methods:

open	(-- okay?)	Prepare this device for subsequent use.
close	(--)	Close this previously **open**ed device.
read	(addr len -- actual)	Read device into memory buffer; return actual byte count.
write	(addr len -- actual)	Write memory buffer to device; return actual byte count.
seek	(pos.lo pos.hi -- status)	Set device position for next **read** or **write**.

Any package that uses the "**deblocker**" support package must define the following methods, which the deblocker uses as its low-level interface to the device.

block-size	(-- block-len)	Return "granularity" for accesses to this device.
max-transfer	(-- max-len)	Return size of largest possible transfer.
read-blocks	(addr block# #blocks -- #read)	Read *#blocks*, starting at *block#*, from device into memory.
write-blocks	(addr block# #blocks -- #written)	Write *#blocks* from memory into device, starting at *block#*.
dma-alloc	(size -- virt)	Allocate a memory region for later use.
dma-free	(virt size --)	Free memory allocated with **dma-alloc**.

NOTE—Although, in general, methods for some busses have optional parameters, the method for physical addresses that use the deblocker package shall not require optional parameters.

4.3 Path resolution

Normative change: correct an error in the path resolution procedure that occurs when there is a device alias "a" whose expansion is "/b". IEEE Std 1275-1994 translated "a:0" to "b:0" instead of the correct result "/b:0".

This section defines the process of resolving a *device path* given by a device-specifier. There are three contexts in which this can occur:

— **find-device**. In this context, the intention is to locate the named *device node* and select it as the *active package* without any other side effects.

— **open-dev**. In this context, the intention is to *open* every node named in the path by executing its **open** method, thereby creating an instance chain, and to return the *ihandle* of the node at the tail end of the chain (the node farthest from the root node).

— **execute-device-method**. In this context, the intention is to open every node named in the path *except for the last node*. An instance chain is created, including an instance for the last node, but instead of executing that last node's **open** method, a different method, given as an argument, is executed. Then the open instances are *closed* and the instance chain is destroyed.

The overall structure of the path resolution process is the same in all three contexts. This description shows it as one process with conditional tests at places where the details are context-dependent. However, it need not be implemented that way; for example, each context could be implemented separately.

The process is described in English as a set of procedures, each consisting of steps that are generally executed in order, with the scope of conditional tests shown by indentation and looping structures shown by labels and "go to" lines. It makes liberal use of variable names to identify intermediate data items. The scope of such variables is "global" with respect to the procedures. The use of these variable names does not imply that an implementation must or should use such variables; they are used solely for descriptive purposes. Similarly, the description of the process in terms of procedures does not imply that the implementation should be so structured; the separate procedures were used in the description so that the top-level description would not be unwieldy.

The following notation describes the parsing of pathnames into component parts:

left-split(*string*, "*x*") -> *initial*, *remainder*

String, *initial*, and *remainder* are the names of string variables, and "*x*" is a character.

Left-split divides *string* into two disjoint substrings, setting *initial* to the portion of *string* before the first occurrence of the character "*x*", and *remainder* to the portion of *string* following the first occurrence of the character "*x*". Neither *initial* nor *remainder* contains that first occurrence of "*x*", although *remainder* may contain other later occurrences of that character. If *string* does not contain the character "*x*", *initial* is set to *string* in its entirety, and *remainder* is set to the empty string.

~~right-split(*string*, "*x*") -> *initial*, *remainder*~~

~~Right-split is similar to left-split, except that the division of the string occurs around the last occurrence of the character "*x*", rather than the first.~~

split-before(*string*, "*x*") -> *initial, remainder*

Split-before is similar to left-split, except that if "*x*" occurs in *string*, *remainder* begins with the first occurrence of "*x*" (left-split removes the first occurrence of "*x*" from *remainder*)

split-after(*string*, "*x*") -> *initial, remainder*

Split-after is similar to split-before, except that the division of the string occurs after the last occurrence of the character "x". If "x" occurs in *string*, *initial* ends with "*x*", and *remainder* begins with the first character, if any, following that last occurrence of "*x*". If "*x*" does not occur in *string*, *initial* is set to *string* and *remainder* is set to the empty string.

The use of the preceding notation does not necessarily imply the existence of functions named left-split, split-before, and split-after ~~and right-split~~; it is simply a notational convention. (This standard does define a function **left-parse-string** whose semantics are very similar to left-split, but the details of returning the results are somewhat different.)

In searching for a matching node, the order in which the various *child nodes* are considered is unspecified. At the implementation's discretion, if no match is found among the children, the search may be widened to include the children's children, recursively to any depth.

In the following algorithmic description (4.3.1 through 4.3.5), the text enclosed in boxes is commentary describing the intention of the algorithm. The text outside of the boxes is definitive.

4.3.1 Path resolution procedure (top level procedure)

If the pathname *does not begin with "/", and its first* node name *component is an* alias*, replace the* alias *with its expansion.*

a) If PATH_NAME does not begin with the "/" character,

1) ~~Left-split~~Split-before(PATH_NAME, "/") -> HEAD, TAIL.

2) ~~Left-split~~Split-before(HEAD, ":") -> ALIAS_NAME, ALIAS_ARGS.

3) If ALIAS_NAME matches a defined alias,

i) Replace ALIAS_NAME with its alias value.

ii) If ALIAS_ARGS is not empty:

a) ~~Right-split~~Split-after(ALIAS_NAME, "/") -> ALIAS_HEAD, ALIAS_TAIL.

b) ~~Right-split~~Split-before(ALIAS_TAIL, ":") -> ALIAS_TAIL, DEAD_ARGS.

c) ~~If ALIAS_HEAD is not empty,~~
Concatenate(ALIAS_HEAD, ~~"/",~~ALIAS_TAIL, ALIAS_ARGS) -> ALIAS_~~TAIL~~NAME.

~~d) Concatenate(ALIAS_TAIL, ":", ALIAS_ARGS) -> ALIAS_NAME.~~

iii) ~~If TAIL is empty, replace PATH_NAME with ALIAS_NAME.~~

iv) ~~Otherwise (when TAIL is not empty),~~
Concatenate(ALIAS_NAME, ~~"/",~~ TAIL) -> PATH_NAME.

If the pathname*, after possible alias expansion, begins with "/", begin the search at the root node. Otherwise, begin at the* active package.

b) ~~Otherwise (when~~If the (possibly expanded) PATH_NAME begins with the "/" character),

1) Remove the "/" from PATH_NAME.

2) Set the *active package* to the root node.

c) If there is no active package, exit this procedure, returning **`false`**.

If the pathname*, after possible alias expansion, begins with "/", begin the search at the root node. Otherwise, begin at the* active package.

<<<The remainder of clause 4.3 is unchanged.>>>

5.2.2.2 Fcode-offset

Editorial change: clarify the matching of control-flow primitives for **`case`** and **`if`** constructs.

Either

byte	Encodes an 8-bit signed (two's complement) offset.

or

byte.high byte.low	Encodes a 16-bit signed (two's complement) offset.

A conditional or looping control transfer is represented by a pair of *FCode functions*. An *FCode-offset* specifies the number of bytes in the FCode program between two corresponding components of a control flow construct. The offset is calculated as the number of FCode bytes from the first byte of the offset to the byte just after the "target" of the control transfer. A positive offset corresponds to a transfer of control in the "forward" (towards the end of the FCode program) direction, and a negative offset corresponds to the "backward" (towards the beginning of the FCode program) direction.

The following control transfer pairs are meaningful, with "**. . .**" representing an arbitrary sequence of FCode bytes:

FCode control transfer pair	**Example source construct**
`b(<mark) ... bbranch` *FCode-offset* *T*^ *B*^	**`begin ... again`**
`b(<mark) ... b?branch` *FCode-offset* *T*^ *B*^	**`begin ... until`**
`b?branch` *FCode-offse* **`... b(>resolve)`** *B*^ *T*^	**`if ... then`**
`b?branch` *FCode-offset1* **`...`** **`bbranch`** *Fcode-offset2* **`... b(>resolve)`** *B1*^ *B2*^ *T1*^ *T2*^	**`if ...`** **`else ... then`**
`b(case) ...` **`... b(of)`** *Fcode-offset1* **`... b(endof)`** *FCode-offset2* *B1*^ *B2*^ *T1*^ **`... b(of)`** *Fcode-offset3* **`... b(endof)`** *Fcode-offset4* *B3*^ *B4*^ *T3*^ **`b(endcase)`** *T2*^ *T4*^	**`case ...`** **`... of ... endof`** **`...`** **`... of ... endof`** **`...`** **`endcase`**
`b(do)` *FCode-offset1* **`... b(loop)`** *FCode-offset2*	**`do ... loop`**
`b(do)` *FCode-offset1* **`... b(+loop)`** *FCode-offset2*	**`do ... +loop`**
`b(?do)` *FCode-offset1* **`... b(loop)`** *FCode-offset2*	**`?do ... loop`**
`b(?do)` *FCode-offset1* **`... b(+loop)`** *FCode-offset2* *B1*^ *T2*^ *B2*^ *T1*^	**`?do ... +loop`**

The markers $B^{\wedge}$ and $T^{\wedge}$ show the "branch" and "target" locations used for the calculation of the value of *FCode-offset*. The value is the signed number of FCode bytes between *B* and *T* (positive if *B* is before *T*). *Bn/Tn~~B1/T1~~* ~~are for~~ refer to the corresponding *FCode-offsetn~~1~~* ~~and B2/T2 are for FCode-offset2~~.

NOTE—On some devices, FCode programs are stored with "gaps" between successive FCode bytes. For example, each FCode byte might be stored in the least significant byte of a separate quadlet, in which case it might be necessary to add four to the address to advance to the next FCode byte. This does not affect the calculation of an *FCode-offset*—the offset is in terms of the number of FCode bytes, independent of how those bytes are addressed.

The offset size (whether of 8 bits or 16 bits) is established at the beginning of the FCode program by the particular start code that begins the FCode program. **`version1`** sets the offset size to 8 bits, and the other start codes (**`start0`**, **`start1`**, **`start2`**, and **`start4`**) set the offset size to 16 bits. The offset size may be changed from 8 bits to 16 bits by executing **`offset16`**.

In most cases (the exceptions are **`bbranch`** and **`b?branch`** in interpretation state), the *FCode evaluator* needs only the sign of the offset, not its numerical value. In these cases, the value of the offset is essentially redundant because control transfers are represented by pairs of FCode functions (a branching function and its target). The offset indicates the distance between the branch and its target, but that information can be derived during the FCode evaluation process without needing the offset value. However, standard FCode programs are required to have numerically correct offsets (as described in the above paragraph) for compatibility with existing practice.

6.3.2.5 Control transfer

Normative change: explicitly describe the behavior of the "**`enter`**" and "**`exit`**" client services for the case where the Open Firmware user interface does not exist.

`boot`

`IN:` `[string] bootspec`
`OUT:` `none`

Exits the *client program*, resets the system (as with the command **`reset-all`**), and reboots the system with the device and arguments given by the null-terminated string *bootspec*. The string *bootspec* is interpreted in the same manner as the arguments of the command **`boot`**.

`enter`

`IN:` `none`
`OUT:` `none`

If an IEEE std 1275 user interface exists, exit the client program and e~~E~~nters the Open Firmware command interpreter (e.g., called by the operating system after a console input device abort). The client program may be resumed if the user continues execution with the **`go`** command.

Otherwise, if another user interface exists, transfer control to that interface.

When no user interface exists, return control to the client program.

`exit`

`IN:` `none`
`OUT:` `none`

If an IEEE std 1275 user interface exists, e~~E~~xit~~s from~~ the client program and enter the Open Firmware command interpreter. The execution of the client program may not be resumed.

Otherwise, if another user interface exists, transfer control to that interface.

When no user interface exists, idle.

`chain`

`IN:` `[address] virt, size, [address] entry, [address] args, len`
`OUT:` `none`

Frees *size* bytes of memory starting at virtual address *virt*, then executes another client program beginning at address *entry*. The argument buffer *args, len* is copied into the Open Firmware memory and passed to the other program. The address of the arguments in the Open Firmware memory is the client program's second argument, and their length is its third argument. `chain` is used to free any remaining memory for a secondary boot program and begin executing the booted program.

NOTE—The behavior of the `chain` *client interface service* includes the functions of **`init-program`** and **`go`** on behalf of the new client program, but does not include the functions of reading the client program into memory, parsing its header, or allocating its memory.

6.3.2.6 User interface

Normative change: define the format of arguments whose existance was implied in IEEE Std 1275-1994 but which were unintentionally not specified.

```
interpret
      IN:   [string] cmd, stack-arg1, ..., stack-argP
      OUT:  catch-result, stack-result1, ..., stack-resultQ
```

Pushes one less than *N-args* items, *stack-arg1*, ..., *stack-argP*, onto the Forth data stack, with *stack-arg1* on top of the stack; executes the null-terminated string *cmd* as a Forth command line guarded by **`catch`**. Pops the result returned by **`catch`** into *catch-result*. If that result is nonzero, restore the depth of the Forth data stack to its depth prior to the execution of `interpret`. If that result is zero, pops up to one less than *N-returns* items, *stack-result1*, ..., *stack-resultQ*, from the Forth data stack into the returned values portion of the argument array, with *stack-result1* corresponding to the top of the stack.

N-args and *N-returns* are stored in the argument array and may be different for different calls to `interpret`. If the number of items *X* left on the Forth data stack as a result of the execution of *cmd* is less than *N-returns*, only *stack-result1, ..., stack-resultX* are modified; other elements of the returned values portion of the argument array are unaffected. If *X* is more than *N-returns*, additional items are popped from the Forth data stack after setting *stack-result1, ..., stack-resultQ* so that, in all cases, the execution of `interpret` results in no net change to the depth of the Forth data stack.

An implementation shall allow at least six *stack-arg* and six *stack-result* items.

`interpret` is optional; it need be present only if the Open Firmware user interface is present.

```
set-callback
      IN:   [address] newfunc
      OUT:  [address] oldfunc
```

Client programs may define a routine for handling the Open Firmware routines **`callback`** and **`sync`**. *Newfunc* is the address of the entry point of the callback routine. This service sets the callback handler to *newfunc* and returns as *oldfunc* the address of the entry point of the previously installed callback handler.

The Open Firmware shall use the same calling conventions specified in 6.3.1 for *client interface services* when calling the callback handler function. See **`callback`** and **`$callback`** glossary entries for details.

A client program callback handler shall return either a nonzero error code in the *ret1* cell of the argument array if the service indicated by the service argument is unavailable, or zero otherwise. The client program callback handler shall return any additional results in the *ret2 ... retN* cells, setting *N-returns* to the total number of return values including the error code (or zero) that is in the *ret1* cell. The handler shall not store more than *M* results, where *M* is the value that was in the *N-returns* cell when the handler was called, nor shall the returned value of *N-returns* exceed *M*.

```
set-symbol-lookup
      IN:   [address] sym-to-value, [address] value-to-sym
      OUT:  none
```

Sets the symbol table resolution **`defer`** words **`sym>value`** and **`value>sym`** so that they execute the client program callbacks whose addresses are given by the arguments *sym-to-value* and *value-to-sym*, respectively. If either argument is zero, the corresponding **`defer`** word is set to the action of **`false`**.

sym-to-value is called as follows:

```
      IN:   [string] symname
      OUT:  error, symvalue
```

The `service` name string in the argument array is a pointer to a null-terminated string containing "`sym-to-value`".

Searches for a symbol whose name is *symname*. If such a symbol is found, returns zero in *error* and the symbol's value in *symvalue*. If no such symbol is found, returns –1 in *error* and zero in *symvalue*.

value-to-sym is called as follows:

```
IN:   symvalue
OUT:  offset, [string] symname
```

The `service` name string in the argument array is a pointer to a null-terminated string containing "`value-to-sym`".

Locates the symbol whose value is closest to but not greater than *symvalue* and returns *offset*, the non-negative offset from the value of that symbol to *symvalue*, and *symname*, the symbol name. If *symvalue* is less than the value of any known symbol, or is insufficiently close to any symbol value according to an implementation-dependent criterion, returns –1 in *offset* and the empty string in *symname*.

`set-symbol-lookup` is optional; it need be present only if the Open Firmware user interface is present and the Client Program Debugging *command group* (see 7.6) is implemented.

Annex A. Open Firmware glossary

Changes to glossary definitions are described for each definition.

Editorial change: use more precise language to describe the bit significance and intended requirements.

`bljoin` (b1.lo b2 b3 b4.hi -- quad) F 0x7F

Join four bytes to form a quadlet.

~~The high bits of each of the four bytes must be zero.~~

Combine the eight least significant bits of each operand to form a quadlet. Other operand bits shall be zero.

Editorial change: clarify the language of the definition.

`b(<mark)` (F: --) F 0xB1

Target of backward branch implemented with **`bbranch`** or **`b?branch`**.

FCode evaluation: (F: --)

Perform the interpretation or compilation semantics of **`begin`**.

FCODE ONLY (Tokenized by **`begin`**)

Editorial change: clarify the language of the definition.

Normative change: correct an error for the case where the **else** clause of the Fcode equivalent of an **if** ... **else** ... **then** construct is executed in Fcode interpretation state.

b(>resolve) (--) F 0xB2

(F: --)

Target of forward branch implemented with **bbranch** or **b?branch**.

FCode evaluation: (F: --)

If in interpretation state:

Do nothing

If in compilation state:

Perform the compilation semantics of **then**. Then, if the current definition is temporary and the depth of the control flow stack is the same as its depth when the temporary current definition was initiated, perform the FCode evaluation semantics of **b(;)** and execute the temporary current definition.

FCODE ONLY (Tokenized by **else**, **then**, and **repeat**)

Editorial change: use more precise language to describe the bit significance and intended requirements.

bwjoin (b.lo b.hi -- w) F 0xB0

Join two bytes to form a doublet.

~~The high bits of each of the two bytes must be zero.~~

Combine the eight least significant bits of each operand to form a doublet. Other operand bits shall be zero.

Editorial change: correct typos in the stack diagrams.

encode-int (quad ~~n~~ -- prop-addr 4 ~~prop-len~~) F 0x111

Encode a number into a *prop-encoded-array*.

The *property encoding* of a (quadlet) number is a sequence of 4 bytes, with the most significant byte first (i.e., at the smallest address).

No alignment is implied; the sequence of 4 bytes begins at the first available location.

Used as: `5000 encode-int ( prop-addr 4 ~~prop-len~~ )`

Editorial change: correct a typo.

find-package (name-str name-len -- false | phandle true) F 0x204

Locate the support package named by *name string*.

If the package can be located, return its *phandle* and **true**; otherwise, return **false**.

Interpret the name in *name string* relative to the "**/packages**" device node. If there are multiple packages with the same name (within the "**/packages**" node), return the *phandle* for the most recently created one.

Editorial change: clarify the description of *xt*.

Normative change: add explicit error-handling requirement to the display driver's open routines and add a required return value. (Historical implementations had such a return value, but IEEE Std 1275-1994 neglected to mention it.)

is-install (xt --) F 0x11C

Create **open**, other methods for this display device.

Create methods for accessing the display device driver in the *active package*. *xt* is the execution token of a routine to initialize the display device, whose stack diagram is (--).

Used as: `['] my-open-routine is-install`

Create the following methods:

open

When later called, execute the display driver's "my-open-routine" (whose execution token is *xt*) guarded by **catch**. If the execution of *xt* results in a **throw**, return **false**. Otherwise, ~~and~~ initialize the *terminal emulator* and return **true**.

write

When later called, pass its argument string to the *terminal emulator* for interpretation.

draw-logo

When later called, execute the display driver's "my-draw-logo" procedure which was installed into the **defer** word **draw-logo** by the driver's "my-open-routine".

restore

When later called, execute the display driver's "my-reset-screen" procedure which was installed into the **defer** word **reset-screen** by the driver's "my-open-routine".

Editorial change: use more precise language to describe the bit significance and intended requirements.

lbsplit (quad -- b.lo b2 b3 b4.hi) F 0x7E

Split a quadlet into 4 bytes.

~~The high bits of the 4 bytes are zero.~~

All but the least significant eight bits of each result value shall be zero.

Editorial change: use more precise language to describe the bit significance and intended requirements.

lwsplit (quad -- w1.lo w2.hi) F 0x7C

Split a quadlet into two doublets.

~~The high bits of the two doublets are zero.~~

All but the least significant sixteen bits of each result value shall be zero.

Normative change: correct the return value of a network device's **read** method for consistancy with historical implementations.

"**network**" S

Packet-oriented network device type.

Standard string value of the "**device_type**" property for network devices with IEEE 802 packet formats.

A standard package with this "**device_type**" property value shall implement the following methods.

open, **close**, **read**, **write**, **load**

Additional requirements for the **open** method:

Execute **mac-address** and create a "**mac-address**" property with that value.

Additional requirements for the **read** method:

Receive (non-blocking) a network packet, placing at most the first *len* bytes of that packet into memory starting at *addr*. Return the number of bytes actually received (not the number copied into memory), or -2 ~~zero~~ if no packet is currently available.

Discard packets containing hardware-detected errors, as though they were not received.

NOTE—In general, -2 indicates no data was available at the time **read** was done and -1 indicates that an error occurred. Zero is generally used only for devices where data arrives in records, packets, or other such container, and indicates that a valid but empty container was received.

Additional requirements for the **write** method:

Transmit the network packet of length *len* bytes from the memory buffer beginning at *addr*. Return the number of bytes actually transmitted.

The packet to be transmitted begins with an IEEE 802 Media Access Control (MAC) header.

Usage restriction: The caller must supply the complete header; the source hardware address will not necessarily be "automatically inserted" into the outgoing packet.

Additional requirements for the **load** method:

Read the default client program into memory, starting at *addr*, using the default network booting protocol.

A standard package with this "**device_type**" property value may implement additional device-specific methods.

A standard package with this "**device_type**" property value shall implement the following property if the associated device has a preassigned IEEE 802.3-style MAC (network) address:

"**local-mac-address**"

NOTE—Such packages often use the "**obp-tftp**" support package to implement the "**load**" method.

See also: "**address-bits**", "**max-frame-size**"

Editorial change: clarify the behavior of **next-property** when various unusual circumstances are encountered.

next-property (previous-str previous-len phandle -- false | name-str name-len true) F 0x23D

Return the *name* of the property following *previous* of *phandle*.

~~*Name* is a null-terminated string that is the name of the property following *previous* in the property list for device *phandle*. If *previous* is zero or points to a zero-length string, *name* is the name of the *phandle's* first property. If there are no more properties after *previous* or if *previous* is invalid (i.e., names a property that does not exist in *phandle*), *name* is a pointer to a zero-length string.~~

Locate, within the property list of the package identified by *phandle*, the first property if *previous-len* is zero, or the property following the property named by the text string *previous-str previous-len* otherwise. Return *name-str name-len* and **true** if such a property exists, or **false** otherwise (i.e. if there are no more properties, or if there is no property in that package with the name given by *property-str property-len*).

A sequence of invocations of **next-property** with the same *phandle* value, beginning with *previous-len* equal to zero, and passing the *name-str name-len* result of the previous invocation as the *previous-str previous-len* argument to the next invocation, continuing until **false** is returned, shall enumerate the names of all properties of that package. The order in which those individual properties are returned is undefined (e.g. the first property returned by **next-property** is not necessarily the one that was created first). If a new property is created within that package between invocations of **next-property** in such a sequence, the new property name may, but need not, be returned as a result of one of the following invocations of **next-property** within that same sequence.

Normative change: add a method that additional experience with IEEE Std 1275-1994 has shown to be required.

"**page-size**" S

MMU package property name to define the virtual address space page size.

prop-encoded-array:

Integer encoded as with **encode-int**.

The value of this property is the number of bytes in the smallest mappable region of virtual address space.

Editorial change: improve a possibly misleading short description.

"**ranges**" S

Standard *property name* to define a bus-specific address translation. ~~device's physical address.~~

<<remainder of glossary entry for "**ranges**" is unchanged>>

Editorial change: add a note to describe the recommended technique for using existing standard words to handle bus-dependent register access semantics.

rb! (FCode function) (byte addr --) F 0x231

Store a byte to device register at *addr*.

Data is stored with a single access operation and flushes any intervening write buffers, so that the data reaches its final destination before the next FCode function is executed.

Register is stored with identical bit ordering as the input stack item.

NOTE—A bus device can substitute (as with **set-token**) a bus-specific implementation of **rb!** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. See clause 3.6.4.2 for further details and for user interface semantics.

Normative change: remove a user interface word that in some situations cannot be implemented properly. Implementations may continue to support it, but its presence is no longer required.

~~**rb!** (user interface) (byte addr --)~~

~~Store a byte to device register at *addr*.~~

~~**Compilation:** (--)~~

~~Perform the equivalent of the phrase:~~

```
h# 231 get-token if execute else compile, then
```

~~**Interpretation:** (byte addr --)~~

~~Perform the equivalent of the phrase:~~

```
h# 231 get-token drop execute
```

~~**NOTE—**A bus device can substitute (see **set-token**) a bus-specific implementation of **rb!** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. The given user interface semantics of **rb!** ensure that such substitutions are visible at the user interface level.~~

Editorial change: add a note to describe the recommended technique for using existing standard words to handle bus-dependent register access semantics.

rb@ (FCode function) (addr -- byte) F 0x230

Fetch a byte from device register at *addr*.

Data is read with a single access operation.

Result has identical bit ordering as the original register data.

NOTE—A bus device can substitute (as with **set-token**) a bus-specific implementation of **rb@** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. See clause 3.6.4.2 for further details and for user interface semantics.

Normative change: remove a user interface word that in some situations cannot be implemented properly. Implementations may continue to support it, but its presence is no longer required.

~~**rb@** (user interface) (addr -- byte)~~

~~Fetch a byte from device register at *addr*.~~

~~**Compilation:** (--)~~

~~Perform the equivalent of the phrase:~~

```
h# 230 get-token if execute else compile, then
```

~~**Interpretation:** (addr -- byte)~~

~~Perform the equivalent of the phrase:~~

```
h# 230 get-token drop execute
```

~~**NOTE—**A bus device can substitute (see **set-token**) a bus-specific implementation of **rb@** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. The given user interface semantics of **rb@** ensure that such substitutions are visible at the user interface level.~~

Editorial change: add a note to describe the recommended technique for using existing standard words to handle bus-dependent register access semantics.

`rl!` (FCode function) (quad qaddr --) F 0x235

Store a quadlet to device register at *qaddr*.

Data is stored with a single access operation and flushes any intervening write buffers, so that the data reaches its final destination before the next FCode function is executed.

Register is stored with identical bit ordering as the input stack item.

NOTE—A bus device can substitute (as with **`set-token`**) a bus-specific implementation of **`rl!`** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. See clause 3.6.4.2 for further details and for user interface semantics.

Normative change: remove a user interface word that in some situations cannot be implemented properly. Implementations may continue to support it, but its presence is no longer required.

~~**`rl!`** (user interface) (quad qaddr --)~~

~~Store a quadlet to device register at *qaddr*.~~

~~**Compilation:** (--)~~

~~Perform the equivalent of the phrase:~~

~~`h# 235 get-token if execute else compile, then`~~

~~**Interpretation:** (quad qaddr --)~~

~~Perform the equivalent of the phrase:~~

~~`h# 235 get-token drop execute`~~

~~**NOTE—**A bus device can substitute (see **`set-token`**) a bus-specific implementation of **`rl!`** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. The given user interface semantics of **`rl!`** ensure that such substitutions are visible at the user interface level.~~

Editorial change: add a note to describe the recommended technique for using existing standard words to handle bus-dependent register access semantics.

`rl@` (FCode function) (qaddr -- quad) F 0x234

Fetch a quadlet from device register at *qaddr*.

Data is read with a single access operation.

Result has identical bit ordering as the original register data.

NOTE—A bus device can substitute (as with **`set-token`**) a bus-specific implementation of **`rl@`** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. See clause 3.6.4.2 for further details and for user interface semantics.

Normative change: remove a user interface word that in some situations cannot be implemented properly. Implementations may continue to support it, but its presence is no longer required.

~~**`rl@`** (user interface) (qaddr -- quad)~~

~~Fetch a quadlet from device register at *qaddr*.~~

~~**Compilation:** (--)~~

~~Perform the equivalent of the phrase:~~

~~`h# 234 get-token if execute else compile, then`~~

~~**Interpretation:** (qaddr -- quad)~~

~~Perform the equivalent of the phrase:~~

~~`h# 234 get-token drop execute`~~

~~**NOTE—**A bus device can substitute (see **`set-token`**) a bus-specific implementation of **`rl@`** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. The given user interface semantics of **`rl@`** ensure that such substitutions are visible at the user interface level.~~

Editorial change: add a note to describe the recommended technique for using existing standard words to handle bus-dependent register access semantics.

rw! (FCode function) (w waddr --) F 0x233

Store a doublet *w* to device register at *waddr*.

Data is stored with a single access operation and flushes any intervening write buffers, so that the data reaches its final destination before the next FCode function is executed.

Register is stored with identical bit ordering as the input stack item.

NOTE—A bus device can substitute (as with **set-token**) a bus-specific implementation of **rw!** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. See clause 3.6.4.2 for further details and for user interface semantics.

Normative change: remove a user interface word that in some situations cannot be implemented properly. Implementations may continue to support it, but its presence is no longer required.

~~**rw!** (user interface) (w waddr --)~~

~~Store a doublet *w* to device register at *waddr*.~~

~~**Compilation:** (--)~~

~~Perform the equivalent of the phrase:~~

```
h# 233 get-token if execute else compile, then
```

~~**Interpretation:** (w waddr --)~~

~~Perform the equivalent of the phrase:~~

```
h# 233 get-token drop execute
```

~~**NOTE—**A bus device can substitute (see **set-token**) a bus-specific implementation of **rb!** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. The given user interface semantics of **rb!** ensure that such substitutions are visible at the user interface level.~~

Editorial change: add a note to describe the recommended technique for using existing standard words to handle bus-dependent register access semantics.

rw@ (FCode function) (waddr -- w) F 0x232

Fetch a doublet *w* from device register at *waddr*.

Data is read with a single access operation.

Result has identical bit ordering as the original register data.

NOTE—A bus device can substitute (as with **set-token**) a bus-specific implementation of **rw@** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. See clause 3.6.4.2 for further details and for user interface semantics.

Normative change: remove a user interface word that in some situations cannot be implemented properly. Implementations may continue to support it, but its presence is no longer required.

~~**rw@** (user interface) (waddr -- w)~~

~~Fetch a doublet *w* from device register at *waddr*.~~

~~**Compilation:** (--)~~

~~Perform the equivalent of the phrase:~~

```
h# 232 get-token if execute else compile, then
```

~~**Interpretation:** (waddr -- w)~~

~~Perform the equivalent of the phrase:~~

```
h# 232 get-token drop execute
```

~~**NOTE—**A bus device can substitute (see **set-token**) a bus-specific implementation of **rw@** for use by its children. This is sometimes necessary to correctly implement its semantics with respect to bit-order and write-buffer flushing. The given user interface semantics of **rw@** ensure that such substitutions are visible at the user interface level.~~

Editorial change: use more precise language to describe the bit significance and intended requirements.

wbsplit (w -- b1.lo b2.hi) F 0xAF

Split a doublet *w* into two bytes.

~~The high bits of each of the two bytes are zero.~~

All but the least significant eight bits of each result value shall be zero.

Editorial change: use more precise language to describe the bit significance and intended requirements.

wljoin (w.lo w.hi -- quad) F 0x7D

Join two doublets to form a quadlet.

~~The high bits of each of the two doublets must be zero.~~

Combine the sixteen least significant bits of each operand to form a quadlet. Other operand bits shall be zero.

Annex C (informative). The `tokenizer`

Normative change to informative annex: add tokenizer commands to standardize the beginning and end of tokenizer source code.

C.3.3 Fcode start and end

These commands create an FCode header for the Open Firmware source between them.

fcode-version2 (--) T

Begin tokenizing an Fcode program.

Prepare the tokenizer to tokenize subsequent source text. Output the Fcode# for **start1** followed by an Fcode header. Some of the fields of the Fcode header are filled-in later by **fcode-end**.

FCODE ONLY command.

fcode-end (--) T

Finish tokenizing an Fcode program.

Output the Fcode# for end0. Stop tokenizing the current Fcode program. Replace the checksum and length fields of the Fcode header with the program's checksum and length.

FCODE ONLY command.

Annex E (informative). SCSI host adapter package class

E.6.1 overall.fth

Normative changes to informative annex: fix bugs in the tokenizer source code.

```
\ FCode driver for hypothetical SCSI host adapter

fcode-version2
hex

" XYZI,scsi"          name          \ Name of device node
" XYZI,12346-01"      model         \ Manufacturer's model number
" scsi-2"             device-type   \ Device implements SCSI-2 method set
3 0                   intr          \ Device interrupts on level 3, no vector

external

\ These routines may be called by the children of this device.
\ This card has no local buffer memory for the SCSI device, so it
```

```
\ depends on its parent to supply DMA memory.  For a device with
\ local buffer memory, these routines would probably allocate from
\ that local memory.

: dma-alloc    ( n -- vaddr )  " dma-alloc" $call-parent  ;
: dma-free     ( vaddr n -- )  " dma-free" $call-parent  ;
: dma-sync     ( vaddr devaddr n -- )  " dma-sync" $call-parent  ;
: dma-map-in   ( vaddr n cache? -- devaddr )  " dma-map-in" $call-parent  ;
: dma-map-out  ( vaddr devaddr n -- )  " dma-map-out" $call-parent  ;
: max-transfer ( -- n )
   " max-transfer"  ['] $call-parent catch  if  2drop h# 7fff.ffff  then
   \ The device imposes no size limitations of its own; if it did, those
   \ limitations could be described here, perhaps by executing:
   \    my-max-transfer min
;


fload scsiha.fth

fload hacom.fth

   new-device
      fload scsidisk.fth  \ scsidisk.fth also loads scsicom.fth
   finish-device

   new-device
      fload scsitape.fth  \ scsitape.fth also loads scsicom.fth
   finish-device

fcode-end
end0
```

E.6.2 scsiha.fth

Normative changes to informative annex: fix bugs in the tokenizer source code.

<<<the code in E.6.2 prior to `(exec)` is unchanged>>>

```
\ Returns true if select failed
: (exec)  ( dma-adr,len dir cmd-adr,len -- hwresult )
   reset-wait           \ Delay until any prior reset operation is done.

   his-lun h# 80 or  regs >message-out rb! \ Set unit number; no disconnect.
   my-id      regs >host-selectid   rb!    \ Set the selection IDs.
   his-id     regs >target-selectid rb!

   \ Write the command block into the host adapter's command register

   dup 0  ?do                       ( data-adr,len dir cmd-adr,len )
      over i + c@                   ( data-adr,len dir cmd-adr,len cmd-byte )
      regs >cmd-adr i ca+ rb!       ( data-adr,len dir cmd-adr,len )
   loop                             ( data-adr,len dir cmd-adr,len )

   regs >cmd-len rl!   drop         ( data-adr,len dir )

   my-id 7 + to my-id               ( initialize for this instance )

   \ Set the data transfer parameters.

   ( .. dir ) regs >input?   rb!    ( data-adr,len )  \ Direction
   ( .. len ) regs >data-len rl!    ( data-adr )      \ Length
   ( .. adr ) regs >data-adr rl!    ( )               \ DMA Address

   \ Now we're ready to execute the command.

```

```
   1  regs >start  rb!                    \ Tell board to start the command.

   get-msecs scsi-time +  to time-limit   \ Set the time limit.

   begin  regs >start rb@  while          \ Wait until command finished.

      scsi-time  if                       \ If timeout is enabled, and
         get-msecs time-limit -  0>=  if  \ the time-limit has been reached,
            reset-scsi-bus  true  exit    \ reset the bus and return error.
         then
      then

   repeat

   \ Nonzero phase means that the command didn't finish.

   regs >phase rb@
;
```

<<<the remainder of E.6.2 is unchanged>>>

E.6.3 hacom.fth

Normative changes to informative annex: fix bugs in the tokenizer source code.

<<<the code in E.6.3 prior to `diagnose` is unchanged>>>

```
external

: diagnose  ( -- error? )
   0 0 true  test-unit-rdy-cmd 6   -1   ( dma$ dir cmd$ #retries )
   retry-command  if                    ( [ sensebuf ] hardware-error? )
      ." Test unit ready failed - "     ( [ sensebuf ] hardware-error? )
      if                                ( )
         ." hardware error (no such device?)" cr          ( )
      else                              ( sensebuf )
         ." extended status = " cr      ( sensebuf )
         base @ >r  hex                 ( sensebuf )
         8 bounds ?do  i 3 u.r  loop cr ( )
         r> base !
      then
      true
   else
      send-diagnostic  ( fail? )
   then
;

headers
```

E.6.4 scsicom.fth

Normative changes to informative annex: remove unnecessary code that refers to a draft version of IEEE Std 1275-1994.

<<<the code in E.6.4 prior to `selftest` is unchanged>>>

```
headerless
: selftest  ( -- error? )
   fcode-revision h# 3.0000 >=  if
      my-unit " set-address" $call-parent
      " diagnose" $call-parent
```

```
   else
      0
   then
;

headers
```

E.6.5 scsidisk.fth

Normative changes to informative annex: fix bugs in the tokenizer source code.

<<<the code in E.6.5 prior to `r/w-blocks` is unchanged>>>

```
: r/w-blocks  ( addr block# #blks input? command -- actual# )
   cmdbuf d# 10 erase
   3 pick  h# 100000 u>=  2over h# 100 u>
   swap h# 200000 u>=  or if  \ Use 10-byte form  ( addr block# #blks dir cmd )
      h# 20 or  0 cb!  \ 28 (read) or 2a (write)  ( addr block# #blks dir )
      -rot swap                                   ( addr dir #blks block# )
      cmdbuf 2 + 4c!                              ( addr dir #blks )
      dup cmdbuf 7 + 2c!
      d# 10                                       ( addr dir #blks cmd-len )
   else                        \ Use 6-byte form  ( addr block# #blks dir cmd )
      0 cb!                                       ( addr block# #blks dir )
      -rot swap                                   ( addr dir #blks block# )
      cmdbuf 1+ 3c!                               ( addr dir #blks )
      dup 4 cb!                                   ( addr dir #blks )
      6                                           ( addr dir #blks cmd-len )
   then
   tuck  >r >r                  ( addr input? #blks ) ( R: #blks cmd-len )
   /block *  swap cmdbuf r> -1      ( addr #bytes input? cmd cmd-len #retries )
   retry-command  if                ( [ sensebuf ] hw? )
      0= if  drop  then  r> drop 0
   else                             (  )
      r>
   then                             ( actual# )
;
```

<<<the remainder of the code in E.6.5 is unchanged>>>

Annex G (informative). Summary lists

G.2 Assigned FCode numbers

Editorial change: correct typo in the specified table entry.

0x121† **display-status**

Annex H (informative). Historical notes

H.4 New FCodes and methods

Editorial change: correct typo.

Most pre-Open Firmware systems do not implement the following FCodes and *methods*:

FCode#	Name	Comments
0xC7	**#**	Not the same as old **#** (now called **u#**).
0xC9	**#>**	Not the same as old **#>** (now called **u#>**).
0xC8	**#s**	Not the same as old **#s** (now called **u#s**).
0xDE	**behavior**	
0x23E	**byte-load**	On pre-Open Firmware, **" byte-load" $find** could be used.
0xDD	**compile,**	On pre-Open Firmware, **" (compile)" $find** could be used.
0x128	**decode-phys**	
0xDA	**get-token**	
method	**encode-unit**	
0x227	**lbflip**	
0x228	**lbflips**	
0x2269	**lwflip**	On pre-Open Firmware, the "**wflip**" tokenizer macro was used.
0x23D	**next-property**	
0x23F	**set-args**	On pre-Open Firmware, **" set-args" $find** could be used.
0xDB	**set-token**	
0xDC	**state**	On pre-Open Firmware, **" state" $find** could be used.
0x89	**unloop**	

H.6 New user interface commands

Editorial change: remove commands that existed prior to Open Firmware from the list.

Most pre-Open Firmware systems do not implement the following user interface commands.

apply	(... "method-name< >device-specifier< >" -- ???)	Execute named method in the specified package.
char	("text< >" -- char)	Generate numeric code for next character from input buffer.
[char]	(C: [text< >] --) (-- char)	Generate numeric code for next character from input buffer.
~~**close-dev**~~	~~(ihandle --)~~	~~Close device and all of its parents.~~
$create	(E: -- a-addr) (name-str name-len --)	Call **create**; new name specified by *name string*.
environment?	(str len -- false | value true)	Return system information based on input keyword.
fm/mod	(d n -- rem quot)	Divide *d* by *n*.
noshowstack	(--)	Turn off **showstack** (automatic stack display).
parse	(delim "text<delim>" -- str len)	Parse text from the input buffer, delimited by *delim*.
parse-word	("text< >" -- str len)	Parse text from the input buffer, delimited by white space.

~~**(patch)**~~	~~(new-n1 num1? old-n2 num2? xt --)~~	~~Change contents of command indicated by *xt*.~~
postpone	(C: [old-name< >] --) (... -- ???)	Delay execution of the immediately following command.
recurse	(... -- ???)	Compile recursive call to the command being compiled.
s"	([text<">] -- text-str text-len)	Gather the immediately following string.
s>d	(n1 -- d1)	Convert a number to a double number.
sm/rem	(d n -- rem quot)	Divide *d* by *n*, symmetric division.
~~**status**~~	~~(--)~~	~~**defer** word that can be used to modify the user interface prompt.~~

H.7 FCode name changes

Editorial change: add name change omitted in IEEE Std 1275-1994.

The following FCodes names have changed from their pre-Open Firmware versions for clarity and consistency. While this can affect the *tokenizer* and/or user interface behavior, the actual behavior of the function associated with that FCode number has not changed. Existing (already-tokenized) FCode programs that use these FCodes will be unaffected.

Items marked with a * have retained the old name, as a synonym.

Old Name	New Name
#	**u#**
#>	**u#>**
#s	**u#s**
<<	**lshift** *
>>	**rshift** *
attribute	**property**
b(is)	**b(to)**
/c*	**chars** *
ca1+	**char+** *
decode-2int	**parse-2int**
delete-attribute	**delete-property**
eval	**evaluate** *
flip	**wbflip**
get-inherited-attribute	**get-inherited-property**
get-my-attribute	**get-my-property**
get-package-attribute	**get-package-property**

Old Name	New Name
is	**to**
lflips	**lwflips**
map-sbus	**map-low**
na1+	**cell+** *
/n*	**cells** *
not	**invert** *
u*x	**um***
version	**fcode-revision**
wflips	**wbflips**
x+	**d+**
x-	**d-**
xdr+	**encode+**
xdrbytes	**encode-bytes**
xdrint	**encode-int**
xdrphys	**encode-phys**
xdrstring	**encode-string**
xdrtoint	**decode-int**
xdrtostring	**decode-string**
xu/mod	**um/mod**

H.8 User interface name changes

Editorial change: remove names from the list which existed only in some implementations and whose behavior is different than the indicated new name.

The following user interface command names have changed from their pre-Open Firmware versions, with no change in behavior.

Old name	New name
.attributes	**.properties**
cd	**dev**
reset	**reset-all**
~~**select-dev**~~	~~**open-dev**~~
~~**unselect-dev**~~	~~**device-end**~~